

Tactical Power Products - Australia's
Security Power Specialist

High Quality Security Products
Designed, Manufactured and
Supported in Australia

www.tacpower.com.au

PO Box 90 Kurrajong NSW 2758 Australia
Tel: 1300822769 sales@tacpower.com.au



General

RLB1-DPDT is a 12Vdc “buffered” relay with a double pole double throw output (DPDT). Solid state “buffering” of trigger inputs allows RLB1-DPDT to be connected to equipment with limited current sink ability, enabling control of devices drawing up to 1A per pole.

A constant 12Vdc supply must be connected to the terminals marked F & G in Table 1.

The relay may be triggered with a negative or positive voltage applied to terminals A or B (respectively).

By default, both poles of the relay are voltage free “dry” contacts. A positive or negative voltage can be applied to the common of either or both poles by changing the jumper settings (K & L) - Negative to the left or Positive to the right.

RLB1-DPDT is also available as a strip of 8 for multiple output applications (such as lift control) - 12Vdc need only be connected to the first relay in the strip as they are connected on a common bus - order Tactical Part No: RLB8-DP.

Please visit www.tacpower.com.au for additional models.

Input Voltage	12Vdc (11 - 15Vdc)
Configuration	DPDT
Contact Rating	1A @ 30Vdc
Dimensions	30W x 40L x 20H mm

A B C D E




Table 1.	
A	Trigger Input (- Negative)
B	Trigger Input (+ Positive)
C	Pole 2 - Common
D	Pole 2 - Normally Closed
E	Pole 2 - Normally Open
F	12V Input (- Negative)
G	12V Input (+ Positive)
H	Pole 1 - Common
I	Pole 1 - Normally Closed
J	Pole 2 - Normally Open
K	Pole 1 Common Link (- C +)
L	Pole 2 Common Link (- C +)

TACTICAL
POWER PRODUCTS

12Vdc DPDT Buffered Relay

RLB1-DPDT



TPS24-6DC

24Vdc 6A Power Supply with 1.4A Battery Charger



TPS13-5DC

13.5Vdc Power Supply with 1.4A Battery Charger



TIM-01

Universal Digital Timer



© 2016 The contents of this manual are copyright and may not be reproduced without permission of - Tactical Power Products Pty Limited.



PDM5

10 Way Power Distribution Board and Fault Relay

www.tacpower.com.au or ask your Tactical distributor for details